

## CFX-750 Display: Hard and Soft Reset

This support bulletin describes the correct procedures for performing a hard and soft rest on the Trimble® CFX-750™ display.

### Hard reset

When you perform a hard reset, all settings return to the factory defaults. This deletes all saved data, including any field data. To do this:

1. Power down the display and then power it on.
2. Wait until the first status bar at the bottom of the startup screen is three quarters full. ***This happens quickly so be prepared to press and hold the buttons on the back of the display.***



3. Press the power button and **both** brightness control buttons at the same time:



4. When you see a third progress bar that counts up very slowly, one tick at a time, you can release the buttons.  
The hard reset takes approximately 10 minutes – ***do not power down the display during this time.***
5. If at any time you see the light bar LEDs slowly moving back and forth, the buttons were pressed too early. Power down the unit and repeat the procedure.

This document is for informational purposes only and is not a legally binding agreement or offer. Trimble makes no warranties and assumes no obligations or liabilities hereunder.

## Soft reset

When you perform a soft reset, all settings return to the factory defaults. All saved field data remains intact. To do this:

1. Power down the display and then power it on.
2. Wait until the first status bar at the bottom of the startup screen is three quarters full. ***This happens quickly so be prepared to press and hold the buttons on the back of the display.***



3. Press the power button and the top one of the two brightness buttons at the same time:



4. When you see a third progress bar that counts up very slowly, one tick at a time, you can release the buttons.  
The hard reset takes approximately 10 minutes – ***do not power down the display during this time.***
5. If at any time you see the light bar LEDs slowly moving back and forth, the buttons were pressed too early. Power down the unit and repeat the procedure.